

M-7, the new RGB LED fogger from Antari.

Up, Down, Left and Right. The M-7 is a unique design among foggers allowing it to be rigged at any angle without worrying about the fluid being spilt.

The new structure incorporates a compartment especially designed for containing the fluid tank to make transporting easier and more efficient.

Smart auto sensing adjusts the power frequency and voltage automatically according to the power input source.



FEATURES

1. New structure design for multiple angle rigging
2. Auto sense frequency
3. Fluid tank compartment for ease of transportation
4. Huge output volume with high pigments LED colors
5. Great fit for Stage purpose

DMX Channel Mode

Channel Mode	Channel	Value	Function
8	1	0-4	Fog Off
		5-255	Fog On
	2	0-255	Red 0-100%
	3	0-255	Green 0-100%
	4	0-255	Blue 0-100%
	5	0-255	Chase 1-15
	6	0-255	Chase speed 0-255 step/min
	7	0-255	Dimmer 0-100%
8	0-255	Strobe 1-20Hz	



SPECIFICATIONS

Voltage	AC-100V/120V/220V/230V/240V, 50 Hz / 60 Hz
Breaker	120V, 15A 250V 230V, 9A 250V
Power Consumption	1,550 W
Initial Heat-Up Time	5 mins
Coverage Volume	Height 5 Meters, Width 1 Meter
Max Operating Time	8 seconds burst
Fluid Consumption Rate	150 ml / Min
Tank Capacity	2.4 liter
Control Options	W-2 Wireless Transmitter DMX Master / Slave
Weight	11.5 Kg
Dimensions (mm)	L 345 W 193 H 385.7
Liquid Used	Antari FLC Water-based Fluid